



POWER ELECTRONICS
SL POWER ELECTRONICS CORP.
6050 King Drive, Bldg. A
Ventura, CA 93003 + 805-486-4565
Internet: www.slpower.com



GLC40 SERIES INSTALLATION INSTRUCTIONS

MODEL NUMBERS: GLC40A, GLC40B, GLC40D, and GLC40-X, where X represents the output voltage, which may be any number from 3.3 through 48. Models may or may not be followed by suffix -XXX and/or G, where XXX may be any number from 001 thru 999. The -XXX suffix are used for value added configurations that have no impact on safety and suffix G indicates compliance to RoHS.

RATINGS:

Input: 100-240 V ac, 1.3 A, 50/60 Hz

Output: 40 W max or see table for standard output voltage models.

Model	Watts ¹	Output #1	Output #2	Output #3
GLC40A	40	+5.1 V dc, 3 A	+12 V dc, 2 A	-12 V dc, 0.3 A
GLC40B	40	+5.1 V dc, 3 A	+15 V dc, 2 A	-15 V dc, 0.3 A
GLC40D	40	+5.1 V dc, 3 A	+24 V dc, 1 A	-12 V dc, 0.3 A
GLC40-3.3	26.4	3.3 V dc, 8 A	Notes: 1. Maximum continuous output power at 50 °C - Total of all Outputs. 2. Maximum Relative Humidity 96 %, no condensation. 3. Storage: -40 to +85 °C. Units should be allowed to warm-up under non-condensing conditions before application of power.	
GLC40-5	40	5.0 V dc, 8 A		
GLC40-9	40	9.0 V dc, 4.4 A		
GLC40-12	40	12.0 V dc, 3.3 A		
GLC40-15	40	15.0 V dc, 2.7 A		
GLC40-24	40	24.0 V dc, 1.7 A		
GLC40-28	40	28.0 V dc, 1.4 A		
GLC40-48	40	48.0 V dc, 0.83 A		



SAFETY DECLARATION: SL Power Electronics Corp. declares under our sole responsibility that all models listed above are in conformity with the applicable requirements of EN60950-1 following the provisions of the Low Voltage Directive 73/23/EEC. All models are Certified to be in compliance with the applicable requirements of UL 60950, CSA 22.2 No. 60950 (L3M1), and EN 60950-1 for Pollution Degree 2 environment and Class I TN-S power systems. The outputs of the supplies meet the requirements for SELV and are not an energy hazard.

Protection Class I requires that the ground terminal be bonded to Protective Earth in the end application. Using this terminal for the primary system earthing terminal is not recommended.

Creepage and clearance distances from primary circuits to ground and secondary circuits, as defined in the applicable safety standards, must be maintained after installation to preserve the intended safety.

The maximum operating temperatures of certain safety components, as defined in the applicable safety standards, must not be exceeded after installation to preserve the intended safety. The output power, ambient air temperature and the availability, amount, direction and/or restriction of airflow influence the temperatures of these components.

WARNING! RISK OF FIRE!

A blown fuse is an indication of catastrophic failure of circuit component(s). Repair must be performed by SL Power Electronics Corp. authorized personnel. Fuse F1 must be replaced with T 2 A 250 V (slow blow), UL Listed and CSA Certified type.

EXPLANATION OF SYMBOLS	
	Alternating Current
	Direct Current
	Attention, Consult Accompanying Documents
	Attention, Dangerous Voltages
	Earth (Ground)

C O N N E C T I O N S

J1 Pin		AC Input	Multi-Output Models		Single Output Models	
			J2 Pin	DC Output	J2 Pin	Sense
1	Line		1	Output #2 (+)	1	Output (+)
3	Neutral		2	Output #1 (+)	2	Output (+)
			3	Output #1 (+)	3	Output (+)
			4	Common	4	Common
			5	Common	5	Common
			6	Output #3 (-)	6	Common

CAUTION:

Do not exceed 5 A per contact.

Mating Connectors: Amp P/N 640250-3
Contacts: Amp P/N 770476-1

Amp P/N 640250-6
Amp P/N 770476-1

Amp P/N 640250-6
Amp P/N 770476-1

SL Power Electronics Corp. will not be liable for the safety, reliability or performance of these power supplies if a) any changes, modifications or repairs are carried out by other than authorized agents of SL Power Electronics Corp., or b) the installation of the supply is not in accordance with these installation instructions and the applicable UL, CSA, IEC/EN safety standards.