

## Is Now Part of



## ON Semiconductor®

To learn more about ON Semiconductor, please visit our website at <a href="https://www.onsemi.com">www.onsemi.com</a>

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any EDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officer




January 2014

# FZT749 PNP Low Saturation Transistor

## **Description**

These devices are designed with high-current gain and low saturation voltage with collector currents up to 3 A continuous.



1. Base 2,4. Collector 3. Emitter

## **Ordering Information**

Part Number	Marking	Package	Packing Method
FZT749	749	SOT-223 4L	Tape and Reel

## **Absolute Maximum Ratings**(1),(2)

Stresses exceeding the absolute maximum ratings may damage the device. The device may not function or be operable above the recommended operating conditions and stressing the parts to these levels is not recommended. In addition, extended exposure to stresses above the recommended operating conditions may affect device reliability. The absolute maximum ratings are stress ratings only. Values are at Values are at  $T_A = 25^{\circ}$ C unless otherwise noted.

Symbol	Parameter	Value	Unit
V <sub>CEO</sub>	Collector-Emitter Voltage	-25	V
$V_{CBO}$	Collector-Base Voltage -35		V
V <sub>EBO</sub>	Emitter-Base Voltage	-5	V
I <sub>C</sub>	Collector Current - Continuous -3		Α
T <sub>J</sub> , T <sub>STG</sub>	Operating and Storage Junction Temperature Range -55 to +150		°C

#### Notes:

- 1. These ratings are based on a maximum junction temperature of 150°C.
- 2. These are steady state limits. Fairchild Semiconductor should be consulted on application involving pulsed or low-duty cycle operation.

1

## Thermal Characteristics(3)

Values are at  $T_A = 25^{\circ}C$  unless otherwise noted.

Symbol	Parameter	Max.	Unit
$P_{D}$	Total Device Dissipation	2	W
$R_{\theta JA}$	Thermal Resistance, Junction to Ambient	62.5	°C/W

#### Note:

3. PCB size: FR-4 76 x 114 x 1.57  $\text{mm}^3$  (3.0 inch x 4.5 inch x 0.062 inch) with minimum land pattern size.

## **Electrical Characteristics**

Values are at  $T_A = 25^{\circ}\text{C}$  unless otherwise noted.

Symbol	Parameter	Conditions	Min.	Max.	Unit
BV <sub>CEO</sub>	Collector-Emitter Breakdown Voltage	I <sub>C</sub> = -10 mA	-25		V
BV <sub>CBO</sub>	Collector-Base Breakdown Voltage	I <sub>C</sub> = -100 μA	-35		V
BV <sub>EBO</sub>	Emitter-Base Breakdown Voltage	I <sub>E</sub> = -100 μA	-5		V
I <sub>CBO</sub>	Collector-Base Cut-Off Current	V <sub>CB</sub> = -30 V		-100	nA
		V <sub>CB</sub> = -30 V, T <sub>A</sub> = 100°C		-10	μΑ
I <sub>EBO</sub>	Emitter-Base Cut-Off Current	V <sub>EB</sub> = -4 V		-100	nA
	DC Current Gain <sup>(4)</sup>	$I_C = -50 \text{ mA}, V_{CE} = -2 \text{ V}$	70		
h <sub>FE</sub>		I <sub>C</sub> = -1 A, V <sub>CE</sub> = -2 V	100	300	
		I <sub>C</sub> = -2 A, V <sub>CE</sub> = -2 V	75		
		I <sub>C</sub> = -6 A, V <sub>CE</sub> = -2 V	15		
V <sub>CE</sub> (sat)	Collector-Emitter Saturation Voltage <sup>(4)</sup>	I <sub>C</sub> = -1 A, I <sub>B</sub> = -100 mV		-300	mV
		I <sub>C</sub> = -3 A, I <sub>B</sub> = -300 mV		-600	1110
V <sub>BE</sub> (sat)	Base-Emitter Saturation Voltage <sup>(4)</sup>	I <sub>C</sub> = -1 A, I <sub>B</sub> = -100 mV		-1.25	V
V <sub>BE</sub> (on)	Base-Emitter On Voltage <sup>(4)</sup>	I <sub>C</sub> = -1 A, V <sub>CE</sub> = -2 V		-1	V
C <sub>ob</sub>	Output Capacitance	V <sub>CB</sub> = -10 V, I <sub>E</sub> = 0, f = 1 MHz		100	pF
f <sub>T</sub>	Transition Frequency	$I_C = -100 \text{ mA}, V_{CE} = -5 \text{ V},$ f = 100 MHz	100		MHz

#### Note:

4. Pulse test: pulse width  $\leq 300 \,\mu\text{s}$ , duty cycle  $\leq 2.0\%$ .

## **Physical Dimensions**

## **SOT-223**




Figure 1. MOLDED PACKAGE, SOT-223, 4 LEAD (ACTIVE)

Package drawings are provided as a service to customers considering Fairchild components. Drawings may change in any manner without notice. Please note the revision and/or date on the drawing and contact a Fairchild Semiconductor representative to verify or obtain the most recent revision. Package specifications do not expand the terms of Fairchild's worldwide terms and conditions, specifically the warranty therein, which covers Fairchild products.

Always visit Fairchild Semiconductor's online packaging area for the most recent package drawings: http://www.fairchildsemi.com/dwg/MA/MA04A.pdf.

For current tape and reel specifications, visit Fairchild Semiconductor's online packaging area: <a href="http://www.fairchildsemi.com/packing\_dwg/PKG-MA04A\_BK.pdf">http://www.fairchildsemi.com/packing\_dwg/PKG-MA04A\_BK.pdf</a>.





#### **TRADEMARKS**

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

AccuPower™ F-PFS™ AX-CAP®, **FRFET®** Global Power Resource<sup>SM</sup> BitSiC™ Build it Now™ GreenBridge™ CorePLUS™ Green FPS™ CorePOWER™ Green FPS™ e-Series™ Gmax™  $CROSSVOLT^{\text{\tiny TM}}$ GTO™  $\mathsf{CTL}^{\mathsf{TM}}$ IntelliMAX™

Current Transfer Logic™ IntelliMAX™

DEUXPEED® ISOPLANAR™

Dual Cool™ Making Small Speakers Sound Louder

EcoSPARK® and Better™

EfficientMax™ MegaBuck™

ESBC™ MICROCOUPLER™

MicroFET™

Tairchild® MicroPak™ MicroPak™
Fairchild Semiconductor® MillerDrive™
FACT Quiet Series™ MotionMax™
FACT® mWSaver®
FAST® OptoHiT™

FAST® mWSaver®
FAST® OptoHiT™
FastvCore™ OPTOLOGIC®
FETBench™ OPTOPLANAR®
FPS™

PowerTrench<sup>®</sup> PowerXS™

Programmable Active Droop™

QFET<sup>®</sup>
QS™
Quiet Series™
RapidConfigure™

Saving our world, 1mW/W/kW at a time™

SignalWise™ SmartMax™ SMART START™

Solutions for Your Success™

SPM®
STEALTH™
SuperFET®
SuperSOT™-3
SuperSOT™-6
SuperSOT™-8
SupreMOS®
SyncFET™

Sync-Lock™

SYSTEM

GENERAL®\*

TinyBoost®

TinyBuck®

TinyCalc™

TinyLogic®

TINYOPTO™

TinyPower™

TinyPower™

TinyPWire™

TranSiC™

TriFault Detect™

TRUECURRENT®\*

µSerDes™

SerDes\*
UHC®
UItra FRFET™
UniFET™
VCX™
VisualMax™
VoltagePlus™
XS™

#### **DISCLAIMER**

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN, NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

## LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

- 1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
- A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

### ANTI-COUNTERFEITING POLICY

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, www.fairchildsemi.com, under Sales Support.

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufacturers of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed applications, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handling and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address any warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

### PRODUCT STATUS DEFINITIONS

#### **Definition of Terms**

Definition of Terms			
<b>Datasheet Identification</b>	Product Status	Definition	
Advance Information	Formative / In Design	Datasheet contains the design specifications for product development. Specifications may change in any manner without notice.	
Preliminary	First Production	Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.	
No Identification Needed	Full Production	Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design.	
Obsolete	Not In Production	Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only.	

Rev. 166

<sup>\*</sup> Trademarks of System General Corporation, used under license by Fairchild Semiconductor.

ON Semiconductor and in are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <a href="www.onsemi.com/site/pdt/Patent-Marking.pdf">www.onsemi.com/site/pdt/Patent-Marking.pdf</a>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and exp

## **PUBLICATION ORDERING INFORMATION**

#### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada
Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910
Japan Customer Focus Center
Phone: 81–3–5817–1050

ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative