





Bridge Rectifiers, Fast Recovery

(Continued)

I_O (AMPS)	4.0		6.0		8.0
@ T_A (°C)	50	4.0 @ 25	50	50	50
@ T_C (°C)		8.0 @ 100	100	50	100
I_{FSM} (AMPS)	200	300	150	250	250
CASE	 CASE D	 CASE DM	 CASE CM	 CASE DM	
V_{RRM} (VOLTS)					
100	CBR4F-L010	CBR4MF-L010	CBR6F-010	CBR6MF-L010	CBR8MF-L010
200	CBR4F-L020	CBR4MF-L020	CBR6F-020	CBR6MF-L020	CBR8MF-L020
400	CBR4F-L040	CBR4MF-L040	CBR6F-040	CBR6MF-L040	CBR8MF-L040
600	CBR4F-L060	CBR4MF-L060	CBR6F-060	CBR6MF-L060	CBR8MF-L060
800	CBR4F-L080	CBR4MF-L080	CBR6F-080	CBR6MF-L080	CBR8MF-L080
1000	CBR4F-L100	CBR4MF-L100	CBR6F-100	CBR6MF-L100	CBR8MF-L100
V_F MAX @ I_F	1.3V @ 3.0A	1.3V @ 2.0A	1.3V @ 3.0A	1.3V @ 3.0A	1.3V @ 4.0A
I_R MAX @ V_{RRM}	10 μ A	10 μ A	10 μ A	10 μ A	10 μ A
t_{rr} (100V thru 400V)	200ns	200ns	200ns	200ns	200ns
t_{rr} (600V thru 800V)	300ns	300ns	300ns	300ns	300ns
t_{rr} (1000V)	500ns	500ns	500ns	500ns	500ns

(6-December 2004)

Central[™]
Semiconductor Corp.
www.centalsemi.com

OUTSTANDING SUPPORT AND SUPERIOR SERVICES



PRODUCT SUPPORT

Central's operations team provides the highest level of support to insure product is delivered on-time.

- Supply management (Customer portals)
- Inventory bonding
- Consolidated shipping options
- Custom bar coding for shipments
- Custom product packing

DESIGNER SUPPORT/SERVICES

Central's applications engineering team is ready to discuss your design challenges. Just ask.

- Free quick ship samples (2nd day air)
- Online technical data and parametric search
- SPICE models
- Custom electrical curves
- Environmental regulation compliance
- Customer specific screening
- Up-screening capabilities
- Special wafer diffusions
- PbSn plating options
- Package details
- Application notes
- Application and design sample kits
- Custom product and package development

REQUESTING PRODUCT PLATING

1. If requesting Tin/Lead plated devices, add the suffix " TIN/LEAD" to the part number when ordering (example: 2N2222A TIN/LEAD).
2. If requesting Lead (Pb) Free plated devices, add the suffix " PBFREE" to the part number when ordering (example: 2N2222A PBFREE).

CONTACT US

Corporate Headquarters & Customer Support Team

Central Semiconductor Corp.
145 Adams Avenue
Hauppauge, NY 11788 USA
Main Tel: (631) 435-1110
Main Fax: (631) 435-1824
Support Team Fax: (631) 435-3388
www.centrasemi.com

Worldwide Field Representatives:
www.centrasemi.com/wwreps

Worldwide Distributors:
www.centrasemi.com/wwdistributors

For the latest version of Central Semiconductor's **LIMITATIONS AND DAMAGES DISCLAIMER**, which is part of Central's Standard Terms and Conditions of sale, visit: www.centrasemi.com/terms



<http://www.centrasemi.com>

Product End of Life Notification

PDN ID:	PDN01090
Notification Date:	6/06/18
Last Buy Date:	12/06/18
Last Shipment Date	6/06/19

Summary: The CBR4MF-L010 Fast Recovery Bridge Rectifier is discontinued and now classified as End of Life (EOL).

Although Central Semiconductor Corp. makes every effort to continue to produce devices that have been proclaimed EOL (End of Life) by other manufacturers, it is an accepted industry practice to discontinue certain devices when customer demand falls below a minimum level of sustainability. Accordingly, the following product(s) have been transitioned to End of Life status as part of Central's ongoing Product Management Process. Any replacement products are noted below. The effective date for placing last purchase orders will be six (6) months from the date of this notice and twelve (12) months from the notice date for final shipments, and minimum order quantities may apply. The last purchase and shipment dates may be extended if inventory is available.

<u>Central Part Number</u>	<u>Replacement</u>
CBR4MF-L010	N/A

Central would be happy to assist you by providing additional information or technical data to help locate an alternate source if we have no replacement available. Please email your requests to engineering@centrasemi.com.

DISCLAIMER: This End of Life (EOL) notification is in accordance with JEDEC standard JESD48 - Product Discontinuance. Central Semiconductor Corp. will make every effort to offer life-time buy (LTB) opportunities and/or offer replacement devices to existing customers for discontinued devices, however, one or both may not be possible for all devices. Please contact your local Central Semiconductor sales representative for LTB opportunities/additional information.



http://www.centrasemi.com

Product End of Life Notification

PDN ID:	PDN01008
Notification Date:	11/02/15
Last Buy Date:	5/02/16
Last Shipment Date	11/02/16

Summary: All bridge rectifiers manufactured in the CASE D package are discontinued and now classified as End of Life (EOL).

Although Central Semiconductor Corp. makes every effort to continue to produce devices that have been proclaimed EOL (End of Life) by various manufacturers, it is an accepted industry practice to discontinue certain devices when customer demand falls below a minimum level of sustainability. Accordingly, the following product(s) have been transitioned to End of Life status as part of Central's Product Management Process. Any replacement product will be noted below. The effective date for placing the last purchase order will be six(6) months from the date of this notice and twelve(12) months from the notice date for final shipments; this may be extended if inventory is available.

Central Part Number	Replacement
CBR4-L010	CBR8M-L060
CBR4-L010 W/DC	CBR8M-L060
CBR4-L020	CBR8M-L060
CBR4-L040	CBR8M-L060
CBR4-L060	CBR8M-L060
CBR4-L080	CBR8M-L060
CBR4-L100	CBR8M-L060
CBR4F-L020	N/A
CBR6-L010	CBR8M-L060
CBR6-L020	CBR8M-L060
CBR6-L040	CBR8M-L060
CBR6-L060	CBR8M-L060
CBR6-L080	CBR8M-L060
CBR6-L100	CBR8M-L060

Central would be happy to assist you by providing additional information or technical data to help locate an alternate source if we have no replacement available. Please email your requests to engineering@centrasemi.com.

DISCLAIMER: This End of Life (EOL) notification is in accordance with JEDEC standard JESD48 - Product Discontinuance. Central Semiconductor Corp. will make every effort to offer life-time buy (LTB) opportunities and/or offer replacement devices to existing customers for discontinued devices, however, one or both may not be possible for all devices. Please contact your local Central Semiconductor sales representative for LTB opportunities/additional information.