

NOTES 1 THE RECOMMENDED CLAMP TORQUE OF REF. NO. 6 TO BE 2 TO 2.5N·m.

2 THE RECOMMENDED CLAMP TORQUE OF REF. NO. 10 TO BE 0.2 TO 0.25N·m.

HEXAGONAL WRENCH DRIVER: PB205/1.27(CL150-0066-3)

3 ROTATION EXAMPLES OF REF. NOS. ① AND ⑥ ARE SHOWN.

- 4 SCREW OF REF. NO. ①. ⑥, ① . LOCTITE 263, OR EQUIVALENT . HENKEL JAPAN IS RECOMMENDED TO PREVENT FROM LOOSENING.
- 5 THIS PRODUCT TO BE USED WITH CABLECLAMP, JR13WCC-*X. ** DESIGNATE DIAMETER OF APPLICABLE CABLE.
- 6 THE CABLE PULL AND TWISTING STRENGTH AND OTHER CHARACTERISTICS MAY DIFFER DEPENDING ON THE CABLE STRUCTURE. PLEASE CONFIRM BEFORE THE USE.

5	PHOS	SPHOR BRONZE	Ε	NICKEL PLATING				10	STAINLESS STEEL				
4	PHENOL-FORMALDEHYDE			(BLACK)			UL94V-0	9	ACRYLONITRII	ACRYLONITRILE BUTADIENE RUBBER		ACK)	
3	PHENOL-FORMALDEHYDE			(BLACK)			UL94V-0	8	ACRYLONITRILE BUTADIENE RUBBER		(BLACK)		
2	COP	PER ALLOY		SILVE	R	PLATII	NG 3μm min.	7	BRASS		BLAG	BLACK CHROME PLATING	
1	ALUMINUM ALLOY			BLACK CHROME PLATING				6	BRASS	BLACK CHROME PLATING		ING	
NO.	MATERIAL			FINISH , REMARKS				NO.	MA	TERIAL	FINISH . REMARKS		
UNIT	ГЅ	$\oplus \Box$		CALE	E COUNT DESCRIPTION		OF REV	ISIONS	DESIGNE)	CHECKED	DATE	
m m	1	\text{\$\sigma} \cdot \qu	2	: 1	⋒								
APPROVED : HY. KOBAYASHI 18. 02. 26 DRAWING NO. EDC-110456-31-00											0		

HS HIROSE ELECTRIC CO...LTD.

D

FORM HC0011-5-7 1 2 3 4